

Wartość	Zestaw Code A	Zestaw Code B	Zestaw Code C	Szerokość Pasek/Odstęp P O P O P O
0	SPACE	SPACE	00	2 1 2 2 2 2
1	!	!	01	2 2 2 1 2 2
2	"	"	02	2 2 2 2 2 1
3	#	#	03	1 2 1 2 2 3
4	\$	\$	04	1 2 1 3 2 2
5	%	%	05	1 3 1 2 2 2
6	&	&	06	1 2 2 2 1 3
7	'	'	07	1 2 2 3 1 2
8	(	(	08	1 3 2 2 1 2
9	)	)	09	2 2 1 2 1 3
10	*	*	10	2 2 1 3 1 2
11	+	+	11	2 3 1 2 1 2
12	,	,	12	1 1 2 2 3 2
13	-	-	13	1 2 2 1 3 2
14	.	.	14	1 2 2 2 3 1
15	/	/	15	1 1 3 2 2 2
16	0	0	16	1 2 3 1 2 2
17	1	1	17	1 2 3 2 2 1
18	2	2	18	2 2 3 2 1 1
19	3	3	19	2 2 1 1 3 2
20	4	4	20	2 2 1 2 3 1
21	5	5	21	2 1 3 2 1 2
22	6	6	22	2 2 3 1 1 2
23	7	7	23	3 1 2 1 3 1
24	8	8	24	3 1 1 2 2 2
25	9	9	25	3 2 1 1 2 2
26	:	:	26	3 2 1 2 2 1
27	;	;	27	3 1 2 2 1 2
28	<	<	28	3 2 2 1 1 2
29	=	=	29	3 2 2 2 1 1
30	>	>	30	2 1 2 1 2 3
31	?	?	31	2 1 2 3 2 1
32	@	@	32	2 3 2 1 2 1
33	A	A	33	1 1 1 3 2 3
34	B	B	34	1 3 1 1 2 3
35	C	C	35	1 3 1 3 2 1
36	D	D	36	1 1 2 3 1 3
37	E	E	37	1 3 2 1 1 3
38	F	F	38	1 3 2 3 1 1
39	G	G	39	2 1 1 3 1 3
40	H	H	40	2 3 1 1 1 3
41	I	I	41	2 3 1 3 1 1
42	J	J	42	1 1 2 1 3 3
43	K	K	43	1 1 2 3 3 1
44	L	L	44	1 3 2 1 3 1
45	M	M	45	1 1 3 1 2 3
46	N	N	46	1 1 3 3 2 1
47	O	O	47	1 3 3 1 2 1
48	P	P	48	3 1 3 1 2 1
49	Q	Q	49	2 1 1 3 3 1
50	R	R	50	2 3 1 1 3 1
51	S	S	51	2 1 3 1 1 3
52	T	T	52	2 1 3 3 1 1
53	U	U	53	2 1 3 1 3 1
54	V	V	54	3 1 1 1 2 3
55	W	W	55	3 1 1 3 2 1
56	X	X	56	3 3 1 1 2 1
57	Y	Y	57	3 1 2 1 1 3
58	Z	Z	58	3 1 2 3 1 1
59	[	[	59	3 3 2 1 1 1
60	\	\	60	3 1 4 1 1 1

Wartość	Zestaw Code A	Zestaw Code B	Zestaw Code C	Szerokość Pasek/Odstęp P O P O P O
61	]	]	61	2 2 1 4 1 1
62	^	^	62	4 3 1 1 1 1
63	-	-	63	1 1 1 2 2 4
64	NUL	`	64	1 1 1 4 2 2
65	SOH	a	65	1 2 1 1 2 4
66	STX	b	66	1 2 1 4 2 1
67	ETX	c	67	1 4 1 1 2 2
68	EOT	d	68	1 4 1 2 2 1
69	ENQ	e	69	1 1 2 2 1 4
70	ACK	f	70	1 1 2 4 1 2
71	BEL	g	71	1 2 2 1 1 4
72	BS	h	72	1 2 2 4 1 1
73	HT	i	73	1 4 2 1 1 2
74	LF	j	74	1 4 2 2 1 1
75	VT	k	75	2 4 1 2 1 1
76	FF	l	76	2 2 1 1 1 4
77	CR	m	77	4 1 3 1 1 1
78	SO	n	78	2 4 1 1 1 2
79	SI	o	79	1 3 4 1 1 1
80	DLE	p	80	1 1 1 2 4 2
81	DC1	q	81	1 2 1 1 4 2
82	DC2	r	82	1 2 1 2 4 1
83	DC3	s	83	1 1 4 2 1 2
84	DC4	t	84	1 2 4 1 1 2
85	NAK	u	85	1 2 4 2 1 1
86	SYN	v	86	4 1 1 2 1 2
87	ETB	w	87	4 2 1 1 1 2
88	CAN	x	88	4 2 1 2 1 1
89	EM	y	89	2 1 2 1 4 1
90	SUB	z	90	2 1 4 1 2 1
91	ESC	{	91	4 1 2 1 2 1
92	FS		92	1 1 1 1 4 3
93	GS	}	93	1 1 1 3 4 1
94	RS	~	94	1 3 1 1 4 1
95	US	DEL	95	1 1 4 1 1 3
96	FNC 3	FNC 3	96	1 1 4 3 1 1
97	FNC 2	FNC 2	97	4 1 1 1 1 3
98	SHIFT	SHIFT	98	4 1 1 3 1 1
99	CODE C	CODE C	99	1 1 3 1 4 1
100	CODE B	FNC 4	CODE B	1 1 4 1 3 1
101	FNC 4	CODE A	CODE A	3 1 1 1 4 1
102	FNC 1			4 1 1 1 3 1
103	Start A			2 1 1 4 1 2
104	Start B			2 1 1 2 1 4
105	Start C			2 1 1 2 3 2
106	Stop			2 3 3 1 1 1 2